

FUCHJAGD-PEILSENDER

Schaltung aus cq-DL 9/2000

Frequenz: 3,5MHz


HF-Leistung: Ca. 3mW / 50 Ohm

Stromaufnahme: Ca. 15mA

Stromversorgung: 9V-Batterie

KENNUNG:

A -> 4 B -> 1 . E  
A -> 2 B -> 1 .. I  
A -> 6 B -> 1 ... S  
A -> 5 B -> 1 .... H  
A -> 3 B -> 1 ..... 5  
A -> 1 B -> 1 ..... \*  
A -> 6 B -> 2 .- A  
A -> 5 B -> 6 ..- U  
A -> 3 B -> 4 ...- D  
A -> 3 B -> 4 ....- B  
A -> 1 B -> 4 .....- 6  
A -> 5 B -> 2 ...- R  
A -> 3 B -> 2 ...- L  
A -> 3 B -> 6 ...- F  
A -> 1 B -> 6 ...- \*  
A -> 1 B -> 5 ...- \*



L 1:

Schalenkern AL160  
A-M: 20Mdg 0,4 CuL  
M-E: 8Mdg

Description:		
Amateur Radio Direction Finder		
HF Transmitter		
Title: ARDF3501		Rev.:
Document No.:		
PlotFile:		
PlotDate: 19.11.2002 22:21:40	Sheet: 1/1	